

Specifications Osram LED driver DALI  
42/220-240/1050 CS | incl. DC Cable for Noxion



[View Product](#)

General Information

|                          |                                                                                                      |
|--------------------------|------------------------------------------------------------------------------------------------------|
| SKU                      | 249399                                                                                               |
| EAN                      | 8719157050838                                                                                        |
| Manufacturer Code        | 8719157050838                                                                                        |
| Brand                    | Osram                                                                                                |
| Manufacturer Name        | (For Noxion)Osram DALI 42/220-240/1050 CS   0.7-1.05A (DIP)   15-42V   incl. DC Cable   Set at 700mA |
| Full box quantity        | 1                                                                                                    |
| Any Lamp all-in warranty | 5 Years                                                                                              |

Technical Information

|                       |                        |
|-----------------------|------------------------|
| Technology            | Accessory              |
| Voltage (V)           | 220-240                |
| Dimmable              | Dimmable with Dali     |
| Output Voltage (V)    | 42                     |
| Type of sensor        | No Sensor              |
| Product Type Category | Accessory - LED Driver |

Dimensions

|             |      |
|-------------|------|
| Length (mm) | 145  |
| Width (mm)  | 43   |
| Height (mm) | 29.5 |

## Why Any-lamp?



Order from the **largest lighting specialist** in Europe



**Customised** quotation



Up to **7 years warranty**



**Easy** return process



Trustpilot

